



Colourful and Connected LED 3-in-1 Printer

Fast printing with flexible connectivity

DCP-L3560CDW



PRINT



SCAN



COPY



2.4GHz

WIRELESS

www.brother.ae

3-in-1 Colour Wireless LED Printer

The colourful and connected DCP-L3560CDW is expertly engineered to quietly deliver high-quality documents without compromising on speed.

A generous paper tray capacity and large Automatic Document Feeder allow you to multitask with ease and keep your office running smoothly.

DCP-L3560CDW



Key features:

- Print up to 26 pages per minute
- 2-Sided print, up to 10 sides per minute
- Scan up to 21 images per minute³
- 8.76cm Colour touchscreen
- Gigabit ethernet, 2.4GHz WiFi and USB
- 512MB Internal memory
- 50 Sheet Automatic Document Feeder (ADF)¹¹
- 250 Sheet paper input tray¹¹
- Comes with 1,000 black, 1,000 colour page yield toners, 3,000 black, 2,300 colour maximum yield available⁸

Quiet without compromise

Print quietly without having to compromise on speed or quality. The DCP-L3560CDW prints full colour pages quickly and flawlessly whilst still being quieter than your average office conversation, making this device perfect for desktop working.

Save time

The expertly designed DCP-L3560CDW has a high capacity paper input and output tray allowing you to print without interruption. The Automatic Document Feeder and 2-sided print feature save you time, enabling you to get on with other tasks.

Effortless

Make your day easier and your printing effortless, with simple set up and gigabit ethernet, 2.4GHz WiFi or USB connection. This efficient DCP-L3560CDW is a breeze to operate using the easy to navigate menu on the 8.76cm colour touchscreen. Benefit from the ability to create custom shortcuts on the touchscreen for your most used functions.

Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The DCP-L3560CDW provides a range of robust features. It uses triple-layer security at a device, network and document level. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.

Print from anywhere



With Brother Mobile Connect, you can fully operate your Brother printer from your fingertips. Print and scan documents on the move and order genuine Brother supplies straight to your door. You can also personalise your frequently used features and unlock a revolutionary way of printing from your mobile device.

Download the app on your mobile device to get started.



General

Technology

Electrophotographic LED

Memory

512MB

Control panel

8.76cm Colour
Touchscreen LCD

Local Interface

Hi-Speed USB 2.0

Wired Network

Gigabit Ethernet

Wireless Network

2.4GHz Support

Carton Contents

Device, Inbox Toners, Drum
Unit, Power Supply Cord,
Quick Set-Up Guide

Print

Print Speed (A4)

1-Sided: 26ppm Mono/Colour
2-Sided: 10 sides per minute
Mono/Colour

FPOT (First Print Out Time)

Up to 13.5 Seconds
Mono/Colour

Quiet Mode

A mode to reduce the printing
noise

Resolution

Up to 600 x 600dpi

Print Languages

PCL5e, PCL5c, PCL6 (PCL XL
Class 3.0), BR-Script3,
PDF Version 1.7

Embedded Fonts (PCL)

73 scalable fonts,
12 bitmap fonts

Embedded Barcodes (PCL)

16 bar codes*

*Code39, Interleaved 2 of 5,
FIM (US-PostNet), Post Net
(US-PostNet) EAN-8, EAN-13,
UPC-A, UPC-E, Codabar, ISBN
(EAN), ISBN (UPC-E), Code128
(set A, set B, set C), EAN128
(set A, set B, set C), Code93,
GS1Databar, MSI

Embedded Fonts (Postscript)

66 scalable fonts

Printer Functions

N-up Printing

Reduce pages into
a single page layout

Poster Printing

Enlarge a single page into a
poster using 2x2, 3x3, 4x4
or 5x5 pages

Watermark Printing

Watermark your documents
with predefined text, custom
logo or custom messages

Manual 2-Sided Print

Manual 2-sided printing
(recommended for media not
supported by automatic
2-sided print)

Print Complete Notice

A printing notification can be
set to go to your computer
(Network only)

Secure Print

Protect print jobs with a 4 digit
release code required at the
device in order for them to
be printed

Universal Print (Microsoft 365)

Print effortlessly with native
Universal Print support on
Brother printers

Printer Driver

Windows

Windows 11
(32 and 64 bit editions)
and more

macOS

Printing via macOS requires the use of AirPrint. Mac drivers are not provided

Linux

CUPS, LPD/LPRng
(x86/x64 environment)

ChromeOS

Supports native
ChromeOS printing

PCL Driver

PCL6 (Standard)

Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother printer

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Paper Handling¹¹

Paper Input

Standard Tray

250 Sheets

Manual Feed Slot

1 Sheet

Automatic Document Feeder (ADF)

50 Sheets

Paper Output

150 Sheets A4

Envelope Printing

Yes from manual feed slot

Media Sizes

Standard Tray

A4, Letter, Legal, Mexico Legal, India Legal, Executive, A5, A5 Long Edge, A6, B5 (JIS), B5 (ISO), B6 (JIS), A4 Short (270mm), Folio, 16K (195x270mm)

Manual Feed Slot

Width 76.2 to 216 mm
Length 116 to 355.6 mm
Envelope; COM-10, DL, C5, Monarch

ADF

Width 105 to 215.9 mm
Length 147.3 to 355.6 mm

Scanner Glass

Up to A4/Letter

Auto 2-Sided

A4

Media Type and Weights

Standard Tray

Plain Paper, Thin Paper, Thick Paper, Recycled Paper, 60 to 163g/m²

Manual Feed Slot

Plain Paper, Thin Paper, Thick Paper, Recycled Paper, Bond, Label, Envelope, Env. Thin, Env.Thick, Glossy Paper, 60 to 163g/m²

ADF

Plain Paper, Thin Paper, Recycled Paper, 60 to 105 g/m²

Auto 2-Sided

Plain Paper, Thin Paper, Recycled Paper, 60 to 105g/m²

Mobile and Web Connectivity

Brother Mobile Connect¹⁷ (Android)

Print from, scan to, preview copies and check the machine status from an Android device

Brother Mobile Connect¹⁷ (iPad / iPhone)

Print from, scan to, preview copies and check the machine status from an iPad / iPhone

Apple AirPrint¹⁷

Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin¹⁷

Print from an Android device without a dedicated App.

Mopria™¹⁷

Print most common file types from Mopria™ supported Android devices

Brother Apps¹⁸

Scan to Mobile, Scan to Searchable PDF, Fax forward to Cloud/E-mail, Scan to PowerPoint, Scan to Excel, Scan to Word, Easy scan to E-mail

Web Connect¹⁸

Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote

Copy

Copy Speed (A4)

1-Sided: 26ppm Mono/Colour

Resolution

Up to 600 x 600dpi

FCOT

(First Copy Out Time)

Up to 14.5 Seconds

Mono/Colour

Grey Scale

256 shades of grey
(8 bit for each colour)

Copy Functions

Multi-Copying/Stack/Sort

Makes up to 999 copies of each page / Stacks or Sorts

Enlargement/Reduction Ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

N in 1 Copying

Allows the user to compress multiple pages on to a single A4 sheet

Scan

Scanner Type

CIS (Contact Image Sensor)

Colour and Mono Scanning

Yes

Scan Speed (A4)³

1-Sided: 27ipm Mono and 21ipm Colour

Scan Resolution from ADF

600 x 600dpi

Scan Resolution from Scanner Glass

1200 x 1200dpi

Interpolated Scan Resolution

Brother Scanner Utility enhances up to 19,200 x 19,200 dpi

Colour Depth

48 bit colour processing (Input)
24 bit colour processing (Output)

Grey Scale

16 bit colour processing (Input)
8 bit colour processing (Output)

Scanner Functions

Supported File Formats

Including PDF (PDF/A, Secure PDF, Signed PDF, Searchable¹⁷) JPEG, TIFF, XPS

Standard Functions¹⁷

Scan to E-mail, OCR, Image and File

Network Scanning

Scan to network folder (SMB)¹⁶, FTP, SharePoint (On Premise)

Scan Profile¹⁵

Create up to 25 preset network, FTP/Sharepoint profiles for an easy way to store multiple scan settings

Document Separation

Create scanned files based on blank sheet separation or a specific number of single sided images or sheets of paper, even if more documents are set on the ADF

Scanner Drivers

Windows

TWAIN and WIA
Windows 10
(32 and 64 bit editions)

macOS

Scanning via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux

SANE (32 and 64 bit editions)

ChromeOS

Supports native ChromeOS scanning

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Fleet Management Tools

BRAdmin Pro^{16,17}

LAN/WAN management software

Driver Deployment Wizard^{16,17}

Easily create print drivers for hassle free deployment over your network

Status Monitor¹⁶

Monitor the status of your machine from your computer

Software

Brother iPrint&Scan Desktop^{15,17}

Print from, scan to, preview copies and check the machine status from Windows or macOS PC

PaperPort SE 14^{16,17}

Document management and sharing program from KOFAX

Utilities

Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

Connectivity

Wired Network

Gigabit Ethernet (10Base-T/100Base-TX/1000Base-T)

Wireless Network

2.4GHz: IEEE 802.11 b/g/n (Infrastructure Mode)
IEEE 802.11 g/n (Wi-Fi Direct)

Wi-Fi Direct[®]

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

Wireless Setup Support

Wi-Fi Protected Setup (WPS)

Wireless Applications

Vertical Pairing

Mobile

Print or scan from your mobile device with Brother Mobile Connect, Airprint, Mopria

Local Interface

Hi-Speed USB 2.0

Security Features

Wired Network Security

APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, SMTP, POP3, IMAP4, FTP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

Wireless Network Security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES)
*Wi-Fi Direct supports WPA2-PSK (AES) only.

APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, FTP, SMTP, POP3, IMAP4), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, POP3, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTP Client, LDAPS, IMAP4, Syslog

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, POP3, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, LDAPS, Web Services (Print/Scan), IMAP4, Syslog

Secure Print

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

Setting Lock

Secures access to the devices control panel by locking it

Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control for up to 100 users

Syslog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

On-Premise Active Directory/LDAP Authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP. Staff can easily use their existing network login credentials to authenticate

Restrict network protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Store Print Log

Allows audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

Supplies and Consumables

Inbox Toner⁸

1 x 1,000 pages (BK)
1 x 1,000 pages (CMY)

Standard Yield Toner⁸

TN279
1,500 pages (BK)
1,000 pages (CMY)

High Yield Toner⁸

TN279XL
3,000 pages (BK)
2,300 pages (CMY)

Drum Unit

DR279CL
Approx 20,000 pages
at 1 page per job

Belt Unit

BU229CL
Approx. 50,000 pages
at 2 pages per job

Waste Toner Box

WT229CL
Approx. 50,000 pages
at 5 pages per job

Dimensions and Weights

With Carton (WxDxH)

497 x 536 x 533mm - 24.0kg

Without Carton (WxDxH)

410 x 444 x 401mm - 20.5kg

Duty Cycle

Recommended Monthly

Up to 3,000 pages

Operating Requirement

Power Requirement

220-240V
AC 50/60Hz

Operating Environment

Humidity 20 - 80 %
10°C - 32.5°C
50°F - 90.5°F

Storage Environment

Humidity 35 - 85 %
0°C - 40°C
32°F - 104°F

Environment

Approx Power

Consumption^{13,23}

Copying: 560W
Copying in quiet mode: 310W
Printing: 560W
Printing in quiet mode: 310W
Ready: 70W
Sleep: 10W
Deep Sleep: 0.6W
Power Off: 0.04W

TEC Value

0.41 kWh/Week

Sound Power¹²

Printing: Mono 6.41B(A)
Colour 6.51B(A)
Ready: Inaudible
Quiet Mode: Mono 5.79B(A)
Colour 5.86B(A)
Deep Sleep: Inaudible

Sound Pressure¹²

PC Printing: Approx. 47.0db(A)
Ready: Inaudible
Quiet Mode: 43.0db(A)

- 3 Scan Speeds based on ISO/IEC 17991
- 8 Approx. declared yield value in accordance with ISO/IEC 19798
- 11 Capacity calculated with 80gsm paper
- 12 Sound pressure and sound power level in accordance with ISO 7779
- 13 Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15 Windows and macOS only
- 16 Windows only
- 17 Optional download
- 18 Requires an Internet connection
- 23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

